Reed Horizontal Bend

INSTALLATION INSTRUCTIONS

Part#: HTLL & HTDL

PARTS/TOOLS NEEDED: Flexible Light Mounting Channel (purchased separately) Power Drill (not provided) Butt Splice Connectors (not provided) #4 Flat Head Screws (not provided) #4 Flat Head Screws (not provided)

SAFETY INSTRUCTIONS

- · Disconnect power before installing, adding or changing any component.
- \cdot To avoid a hazard to children, account for all parts and destroy all packing materials.
- · It is recommended that a 5 Amp standard automotive fuse protection be added to the positive (+) input.
- · The addressable Reed is NOT polarity protected. Wiring the light incorrectly could cause damage.

INSTALLATION CONSIDERATIONS

- Do not bend lighting more than necessary. It should only be bent to a 1" radius. Bending to a tight 90° angle could cause damage to the circuit
- · Only bend the LED ribbon in one natural direction, do not try to bend in an unnatural direction such as twisting.
- Make sure surfaces are smooth, clean and free of dust and debris before installing this product. Failure to properly clean the surface may result in loss of adhesion.
- · Rough surfaces may prevent proper adhesion. If adhesion failure occurs screw-in mounting channels may be used for installation.
- · Contact ITC sales for more information on mounting channel: 616-396-1355 / sales@itc-us.com
- · Electrical specifications: 1.42 W/Ft | 0.11 A/Ft
- Addressable lighting products require harnessing considerations for signal integrity. Please contact an ITC Sales Representative regarding your application and for assistance when designing an aRGB system.
- 1. Determine the installation location of your tape lighting. Lights can be attached via the adhesive on the back or with a mounting channel.

Clean surface with a mixture of 50% water/50% Isopropyl alcohol. Let surface dry. Apply Primer 94 as recommended by 3M*. Failure to follow the surface preparation guidelines will void the warranty.

Mounting channels are available as screw mount. Screws should be used every 12". If there is adhesive on the back of the light, remove before installing in the channel.









*http://www.3m.com/3M/en_US/bonding-and-assembly-us/resources/full-story/?storyid=b3996cbd-9954-455f-8e72-88e452ca38c0

2. Wire the light based on the wiring diagrams below.

Note: Addressable Reed tape light will require one driver (part #810-00719) for every 5.5A of power used. Multiple light lengths can be wired to one driver.



3. Please review the considerations below to ensure a successful installation.





segment / Two 12V segments